

ablerex

800LS

1000LS



Every minute is vital when you have a small business. At any point, you have decisions to make, issues to handle, opportunities to check out.

For you, the only moment that matters is the one you are now living. The last thing you need is a disruption when something happens to the power.

That's why you turn on Ablerex uninterruptible power supply to ensure it stays "all-systems-go". So your time and mind can be better focused on the important of running and growing your business.

Keeps you going with backup power

With up to 30 minutes continuous power, you can go on working during a power shortage. You'll also have enough time to save your work. So you can just pick up where you left off once power resumes.

Protect equipment from fluctuating power

With numerous fluxes in the power supply, your equipment and data are vulnerable to damage or loss. The automatic voltage regulator prevents this by feeding your equipment a stable, constant flow of power - so you can go on working smoothly.

Provide surge protection for modem/network line

Being connected is vital to keeping deadlines and your company's reputation. This feature gives you reassurance your network will be safe from disruptive power surges.

Connects up to 1 workstation or 4 devices

Technical Specifications

		800LS	1000LS
Input	Voltage	160Vac ~ 290Vac	
	Frequency	45Hz ~ 65Hz (Auto-sensing)	
Output (AC mode)	AVR	Increase output 15% (input -9% ~ -25%) Decrease output 15% (input +9% ~ +25%)	
Output (Inv. mode)	Voltage	220Vac +/- 10%	
	Frequency	50/60Hz +/- 1Hz	
	Waveform	Simulated Sine Wave	
	Capacity	800VA/400W	1000VA/600W
	Transfer Time	2ms ~ 6ms Typical	
Backup Time	5 ~ 30mins for typical IT load		
Battery	Voltage	12Vdc	
	Type	Sealed Maintenance-free Lead Acid VRLA Type	
	Capacity	12V/7AH	12V/9AH
	Recharge Time	4 ~ 6 hours (to 90%)	
Function	DC Start	Yes	
	Plug-in Charging	Yes	
	Site Wiring Fault Indicator	Yes	
	Advanced Discharge	Yes	
	Battery Management		
Display	LED (Standard)	3 LEDs for Line, Backup and Fault	

		800LS	1000LS
Protection	Overload AC mode	>100% Input fuse blown and Buzzer continuously sounds	
	Overload Inverter mode	>100% Buzzer continuously sounds until battery cut-off	
	Short Circuit	Shuts down immediately	
	Modem (Optional) Network (Optional)	RJ11 RJ45	
Alarm	Battery mode	Buzzer sounds every 1sec	
	Battery Low	Buzzer sounds every 0.1sec	
Physical	Dimension (W×H×D)	100 × 140 × 292mm	
	Net Weight	4.5kg	5kg
	Output Connection***	4 x Thailand Outlets	
Environment	Operation Temperature	0 ~ 40°C	
	Operation Humidity	95% RH Maximum, Non-condensing	
	Altitude	1000m without Derating	
	Noise Level	≤ 40dB	
Computer Interface	Interface Type (Standard)	USB Communication	
	Interface Type (Optional)	RS232 Communication	
	Compatible Platforms	Microsoft Windows Series, Linux, Mac, etc.	
Standards and Certifications**	Safety Standard	EN62040-2	
	EMC/Surge Standard Mark	EN61000-3-2, EN61000-3-3 CE, RoHS, TISI	
	Quality Management	ISO9001:2008, ISO14001:2008	

*Specifications subject to change without prior notice.

**Depending on the model and voltage, please consult Ablerex for more information.

***Connector types varies between countries, please consult Ablerex for more information.

Designed & Engineered by

Ablerex
every moment counts